

FM

A. You must change the phone from Normal Mode to FM Test mode

B. The command [0 1] (suspend) is entered to start test.

C. You should enter the following keys.

[0 9 X X X X #, 0 7, 9 7 X X X]

- If you enter the command [0 9], You can select the channel.

- The command [0 7] means Carrier On (Carrier Off : 0 8)

- If you enter the command [9 7], You can control the power output level. Following under-bar means AGC code. And you can control the power output level using [SEND] or [END] key

ex) 9 7 4 5

D. Control the TX Power Output Level using [SEND] or [END] key.

When you press [OK] key to store Data in EEPROM, enter next power level control step automatically

LEVEL	LCD Display	TX OUTPUT POWER	STORE
2	TXpwr[02]	+26dBm +.5/-4dB	OK
3	TXpwr[03]	+24dBm +2/-4dB	OK
4	TXpwr[04]	+20dBm +2/-4dB	OK
5	TXpwr[05]	+16dBm +2/-4dB	OK
6	TXpwr[06]	+12dBm +2/-4dB	OK
7	TXpwr[07]	+08dBm +2/-4dB	OK