



FCC CFR 47 Part 90.219 Test Report

APPLICANT	CRESCEND TECHNOLOGIES, LLC
ADDRESS	140 E. State Parkway SCHAUMBURG IL 60173 USA
FCC ID	CWWP25XXHA3
MODEL NUMBER	P25R2HA3-PS1-C8-001
PRODUCT DESCRIPTION	HIGH BAND HIGH POWER AMPLIFIER
DATE SAMPLE RECEIVED	10/17/2019
FINAL TEST DATE	10/24/2019
TESTED BY	Tim Royer
TEST RESULTS	☒ PASS ☐ FAIL

Report Number	Report Version	Description	Issue Date
2803AUT19TestReport_	Rev1	Initial Issue	10/24/2019
	Rev2	The EUT Technical Specification has been updated	11/25/2019

THE ATTACHED REPORT SHALL NOT BE REPRODUCED EXCEPT IN FULL WITHOUT THE WRITTEN APPROVAL OF TIMCO ENGINEERING, INC.

TABLE OF CONTENTS

GENERAL REMARKS	2
GENERAL INFORMATION	3
SUMMARY OF RESULTS.....	4
EMISSION DESIGNATION	5
TEST FREQUENCIES.....	6
INPUT SIGNALS.....	7
4K00F3E (NARROWBAND ANALOG FM VOICE)	8
8K10F1E/F1D (P25 PHASE I C4FM VOICE, DATA).....	9
8K10F1W (P25 PHASE II H-CPM VOICE & DATA).....	10
11K3F3E (NARROWBAND ANALOG FM VOICE)	11
16K0F3E (WIDEBAND ANALOG FM VOICE)	12
AGC THRESHOLD	13
TEST DATA: AGC MEASUREMENT TABLE	14
TEST DATA: AGC MEASUREMENT PLOT	15
OUT OF BAND REJECTION	16
TEST DATA: OUT OF BAND REJECTION, OPERATIONAL BAND AGC	17
TEST DATA: OUT OF BAND REJECTION, OPERATIONAL BAND AGC-3	18
INPUT VS OUTPUT COMPARISON	19
451 MHZ.....	23
460 MHZ.....	33
469 MHZ.....	43
RF POWER OUTPUT	53
TEST DATA: 400 BAND MEASUREMENT TABLE.....	54
POWER TO FINAL AMPLIFIER.....	55
TEST DATA: POWER TO FINAL AMPLIFIER CALCULATION.....	55
NOISE FIGURE.....	56
450 – 470 MHZ BAND NOISE FIGURE	57
INTERMODULATION SPURIOUS EMISSIONS	58
SPURIOUS EMISSIONS AT ANTENNA TERMINALS	59
TEST DATA: CONDUCTED SPURIOUS EMISSIONS BELOW 1 GHZ.....	60
TEST DATA: CONDUCTED SPURIOUS EMISSIONS ABOVE 1 GHZ	61
FREQUENCY STABILITY	62
FIELD STRENGTH OF SPURIOUS EMISSIONS.....	63
451 MHZ RADIATED SPURIOUS EMISSIONS.....	65
460 MHZ RADIATED SPURIOUS EMISSIONS.....	65
469 MHZ RADIATED SPURIOUS EMISSIONS.....	66
STATEMENT OF MEASUREMENT UNCERTAINTY.....	67
EMC EQUIPMENT LIST	68

GENERAL REMARKS

Summary

The device under test does:

- ☒ Fulfill the general approval requirements as identified in this test report and was selected by the customer.
- ☐ Not fulfill the general approval requirements as identified in this test report

Attestations

This equipment has been tested in accordance with the standards identified in this test report. To the best of my knowledge and belief, these tests were performed using the measurement procedures described in this report.

All instrumentation and accessories used to test products for compliance to the indicated standards are calibrated regularly in accordance with ISO 17025 requirements.

I attest that the necessary measurements were made at:

Timco Engineering Inc.
849 NW State Road 45
Newberry, FL 32669
Designation #: US1070

Tested by:



Name and Title	Tim Royer, Project Manager / EMC Engineer
Date	10/24/2019

GENERAL INFORMATION

EUT Definition: FCC 90.219(a)

Signal booster. A device or system that automatically receives, amplifies, and retransmits signals from wireless stations into and out of building interiors, tunnels, shielded outdoor areas and other locations where these signals would otherwise be too weak for reliable communications. Signal booster systems may contain both Class A and Class B signal boosters as components.

EUT Technical Specifications:

EUT Description	HIGH BAND HIGH POWER AMPLIFIER		
FCC ID	CWWP25XXHA3		
Model Number	P25R2HA3-PS1-C8-001		
Operating Frequency	450-454 MHz, 456-462.5375 MHz, 462.7375-467.5375 MHz, 467.7375-470 MHz		
EUT Power Source	☒ 110–120Vac, 50– 60Hz	☐ DC Power	☐ Battery Operated
Test Item	☐ Engineering Prototype	☒ Pre-Production	☐ Production
Type of Equipment	☒ Fixed	☐ Mobile	☐ Portable
Antenna Connector	External, N Type		
Test Conditions	The temperature was 26°C Relative humidity of 50%.		
Modification to the EUT	No Modification to EUT.		
Test Exercise	The EUT was operated in accordance with the service manual using software supplied by the manufacturer.		
Applicable Standards	TIA 603-E:2016, ANSI C63.26, FCC CFR 47 Part 2, Part 90, KDB 935210 D05 v01r02, section 4		
Deviation from Standards	The testing methods for Conducted Spurious Emissions were deviated from in the following ways: The signal was swept throughout the entire operational passband of the device. This enabled the laboratory to determine the worst-case in-band frequencies to be used for Radiated Field Strength of Spurious Emissions.		
Test Facility	Timco Engineering Inc. at 849 NW State Road 45 Newberry, FL 32669 USA. Designation #: US1070		

SUMMARY OF RESULTS

Applied Rule Part(s)	Test	Result
KDB 935210 s.4, FCC Pt. 90.531(a)	Test Frequencies	For Reporting Only
KDB 935210 s.4.1	Input Signals	For Reporting Only
KDB 935210 s.4.2	AGC Threshold	For Reporting Only
KDB 935210 s.4.3, FCC Pt. 90.219(a), FCC Pt. 90.219(d)(7)	Out-of-Band Rejection	CLASS B DEVICE
KDB 935210 s.4.4, FCC Pt. 2.1049(c), FCC Pt. 90.219(e)(4)(ii), FCC Pt. 90.210(c)	Input vs. Output Signal Comparison	PASS
KDB 935210 s.4.4, FCC Pt. 90.543(a),(c),(e)	Adjacent Channel Power	n/a
KDB 935210 s.4.5, FCC Pt. 90.219(e)(1), FCC Pt. 90.219(e)(4)(iii)	RF Power Output (and Gain)	PASS
FCC Pt. 2.1033(c)(8)	Power Input to the Final Power Amplifier	For Reporting Only
KDB 935210 s.4.6, FCC Pt. 90.219(e)(2)	Noise Figure	PASS
KDB 935210 s.4.7.2 FCC Part 2.1051(a), FCC Pt. 90.219(d)(6)(i), FCC Pt. 90.219(e)(3)	Intermodulation Spurious Emissions	n/a
KDB 935210 s.4.7.3, FCC Part 2.1051(a), FCC Pt. 90.219(e)(3)	Spurious Emissions at Antenna Terminals	PASS
KDB 935210 s.4.8, FCC Part 2.1055(a)(1), FCC Part 2.1055(b), FCC Pt. 90.219(e)(4)(i)	Frequency Stability	n/a
KDB 935210 s.4.9, FCC Part 2.1053(a), FCC Pt. 90.219(e)(3)	Field Strength of Spurious Emissions	PASS

EMISSION DESIGNATION

Rule Part No.: FCC Part 2.202(g)

Note: All signals used here are representative of the type of signals which will be passed through this EUT, as outlined in KDB 935210 s.4.1.

Analog Signals

Emission Designator	Description	Modulation Type	M (modulation Freq., kHz)	R (rate, baud)	D (deviation, kHz)	K (numeric constant)	S (symbols)	Bandwidth Calculation	Necessary Bandwidth
4K00F3E	Narrowband Analog FM Voice	FM	1.0	-	1.0	1.0	-	$B_n = 2M + 2DK$	4.00
11K2F3E	Narrowband Analog FM Voice	FM	3.0	-	2.5	1.0	-		11.00
16K0F3E	Wideband Analog FM Voice	FM	3.0	-	5.0	1.0	-		16.00

Digital Signals

Emission Designator	Description	Modulation Type	M (modulation Freq., kHz)	R (rate, baud)	D (deviation, kHz)	K (numeric constant)	S (symbols)	Bandwidth Calculation	B _n (necessary bandwidth, kHz)
4K00F1E	Narrow NXDN Voice	4FSK	-	4800	1.55	0.516	4	$B_n = (R/\log_2 S) + 2DK$	4.00
4K00F1D	Narrow NXDN Data	4FSK	-	4800	1.55	0.516	4		4.00
4K00F1W	Narrow NXDN Voice/Data	4FSK	-	4800	1.55	0.516	4		4.00
8K30F1E	Wide NXDN Voice	4FSK	-	4800	3	0.984	4		8.30
8K30F1D	Wide NXDN Data	4FSK	-	4800	3	0.984	4		8.30
8K30F1W	Wide NXDN Voice & Data	4FSK	-	4800	3	0.984	4		8.30
4K00F2D	Narrow NXDN CW ID	4FSK	0.8	4800	1.2	1.0	4	$B_n = 2M + 2DK$	4.00
8K30F2D	Wide NXDN CW ID	4FSK	1.15	4800	3	1	4		8.30
7K60FXE	DMR Voice	4FSK	-	9600	1.8	0.778	4	$B_n = (R/\log_2 S) + 2DK$	7.60
7K60FXD	DMR Data	4FSK	-	9600	1.8	0.778	4		7.60
8K10F1E	P25 Phase I C4FM Voice	4FSK	-	9600	1.8	0.916	4	$B_n = (R/\log_2 S) + 2DK$	8.10
8K10F1D	P25 Phase I C4FM Data	4FSK	-	9600	1.8	0.916	4		8.10
8K10F1W	P25 Phase II H-CPM Voice/Data	4FSK	-	9600	1.8	0.916	4		8.10

TEST FREQUENCIES

Rule Part No.: KDB 935210 s.4

All tests specified in KDB 935210 D05, Section 4 are intended for each band/block of operation. The bands/blocks of operation of this EUT are as follows:

EUT Operational Band(s): KDB 935210 D02, Appendix D, Table D.3

Table D.3 – Various Part 90 PLMRS band allocations, rule parts/sections, and service types for Section 90.219 purposes (for info only – see rules for details, also KDB Publication 634817 [R14])

F _L (MHz)	–	F _H (MHz)	Rule(s)	Misc. Notes
406.1	–	420	90.265	

Frequencies for Testing: FCC Pt. 90.20(c)(3)

§90.20 Public Safety Pool.

(3) *Frequencies.*

PUBLIC SAFETY POOL FREQUENCY TABLE

Frequency or band	Class of station(s)	Limitations	Coordinator
450 to 470	Fixed, base, or mobile	26, 56	

(26) Assignment of frequencies in this band are subject to the provisions of §90.173. Licensees as of August 18, 1995 who operate systems in the 150-170 MHz band that are 2.5 kHz removed from regularly assignable frequencies may continue to operate on a secondary, non-interference basis after August 1, 2003.

(56) The frequencies available for use at fixed stations in this band and the requirements for assignment are set forth in §90.261. Operation on these frequencies is secondary to stations in the Industrial/Business Pool where they are assigned for land mobile operations.

Frequencies for Testing: FCC Pt. 90.261(c)(3)

§90.261 Assignment and use of the frequencies in the band 450-470 MHz for fixed operations.

(a) Frequencies in the 450-470 MHz band as listed in §§90.20(c)(3) and 90.35(b)(3) may be assigned to all eligibles for fixed use on a secondary basis to land mobile operations.

The EUT will utilize the bands:

450 - 470 Band			
Operation	Band	Test Frequency(ies)	Notes
PLMRS/PSRS	450 - 470 MHz	451, 460 & 469 MHz	

INPUT SIGNALS

Rule Part No.: KDB 935210 s.4.1

The procedures in this clause are specific to EUTs intended for operating in the Private Land Mobile Radio Services (PLMRS) and Public Safety Radio Services (PSRS)⁵, which are governed under the provisions and requirements of the Part 90 rules (i.e., Section 90.219 applies).

Table 1 depicts signal types associated with PLMRS operations, which are to be considered as test signals to be used in performing compliance testing on PLMRS amplifiers, repeaters, and industrial boosters. Not all of the procedures in this clause will require using each of the signals listed in Table 1, because for many EUTs a CW tone can adequately model the narrowband signals typically encountered within these services. For EUTs supporting digitally modulated signals, the intended operating signal types should be tested (e.g., P25 Phase 1, P25 Phase 2, TETRA, etc.), especially for PSRS devices. Devices intended for use in 700 MHz Public Safety Broadband spectrum shall be tested using a representative band-limited AWGN signal (99 % OBW of 4.1 MHz) or the applicable signal type (e.g., LTE).

Table 1—Test signals for PLMRS devices

Emission Designator	Modulation	Occupied Bandwidth	Channel Bandwidth	Audio Frequency
16K0F3E	FM	16 kHz	25 kHz	1 kHz
11K3F3E	FM	11.3 kHz	12.5 kHz	1 kHz
4K00F1E	FM	4 kHz	6.25 kHz	1 kHz
N/A	CW	N/A	N/A	N/A

Note: All input signals are broadcast from an amplifier used to bring the input level to the EUT up to the rated levels. The signal was decreased to 0 dBm (CW) from the test amplifier, and modulation was applied. Actual input levels were higher. Please see RF Power Output section for details.

Input Signals

4K00F3E (Narrowband Analog FM Voice)


Substituted for signals:

4K00F1E (Narrow NXDN Voice)

4K00F1D (Narrow NXDN Data)

4K00F1W (Narrow NXDN Voice & Data)

4K00F2D (Narrow NXDN CW ID)




Date: 1.JAN.1997 02:54:54

Occupied Bandwidth: 4.2 kHz

Input Signals

8K10F1E/F1D (P25 Phase I C4FM Voice, Data)




Date: 1.JAN.1997 02:40:45

Occupied Bandwidth: 7.69 kHz

Input Signals

8K10F1W (P25 Phase II H-CPM Voice & Data)



Date: 1.JAN.1997 02:42:50


Occupied Bandwidth: 7.69 kHz

Input Signals

11K3F3E (Narrowband Analog FM Voice)

Substituted for signals:

7K60FXE (2-Slot DMR TDMA Voice)
 7K60FXD (2-Slot DMR TDMA Data)
 8K30F1E (Wide NXDN Voice)
 8K30F1D (Wide NXDN Data)
 8K30F1W (Wide NXDN Voice & Data)
 8K30F2D (Wide NXDN CW ID)




Date: 1.JAN.1997 02:38:40

Occupied Bandwidth: 7.76 kHz

Applicant: CRESCEND TECHNOLOGIES, LLC
 FCC ID: CWWP25XXHA3
 Report: 2803AUT19TestReport_Rev2

Input Signals

16K0F3E (Wideband Analog FM Voice)



Date: 1.JAN.1997 01:29:49

Occupied Bandwidth: 12.42 kHz

AGC THRESHOLD

Rule Part No.: KDB 935210 s.4.2

Requirements:

Testing at and above the AGC threshold will be required.⁶ The AGC threshold shall be determined by applying the procedure of 3.2, but with the signal generator configured to produce a test signal defined in Table 1, a CW input signal, or a digitally modulated signal, consistent with the discussion about signal types in 4.1.

⁶ See footnote 1 about the terms and concepts AGC, ALC, OLC.

Test Procedure: KDB 935210 s.3.2

The AGC threshold is to be determined as follows.³


In the case of fiber-optic distribution systems, the RF input port of the equipment under test (EUT) refers to the RF input of the supporting equipment RF to optical convertor; see also descriptions and diagrams for typical DAS booster systems in KDB Publication 935210 D02 [R7].

Devices intended to be directly connected to an RF source (donor port) only need to be evaluated for any over-the-air transmit paths.

- a) Connect a signal generator to the input of the EUT.
- b) Connect a spectrum analyzer or power meter to the output of the EUT using appropriate attenuation as necessary.
- c) The signal generator should initially be configured to produce either of the required test signals (i.e., broadband or narrowband).
- d) Set the signal generator frequency to the center frequency of the EUT operating band.
- e) While monitoring the output power of the EUT, measured using the methods of 3.5.3 or 3.5.4, increase the input level until a 1 dB increase in the input signal power no longer causes a 1 dB increase in the output signal power.
- f) Record this level as the AGC threshold level.
- g) Repeat the procedure with the remaining test signal.

³ Consistent with for example TIA-156 [R10], for compliance testing purposes the terms automatic gain control (AGC), automatic level control (ALC), and output level control (OLC) are generally taken to be synonyms, which refer to a means by which gain or output power is electronically adjusted as a function of voltage or some other specified parameter(s).

Test Setup Block Diagram: KDB 935210 s.3.2



AGC THRESHOLD

Test Data: AGC Measurement Table

INPUT (dBm)	CORRECTED INPUT (dBm)	CORRECTED OUTPUT (dBm)	GAIN (dB)
-48	10.38	-23.79	-34.2
-47	11.38	-23.79	-35.2
-46	12.38	-23.79	-36.2
-45	13.38	-23.79	-37.2
-44	14.38	-21.47	-35.9
-43	15.38	-21.47	-36.9
-42	16.38	-21.47	-37.9
-41	17.38	-21.47	-38.9
-40	18.38	-21.47	-39.9
-39	19.38	-21.47	-40.9
-38	20.38	53.29	32.9
-37	21.38	53.41	32.0
-36	22.38	53.41	31.0
-35	23.38	53.41	30.0
-34	24.38	53.41	29.0
-33	25.38	53.41	28.0
-32	26.38	53.41	27.0
-31	27.38	53.41	26.0
-30	28.38	53.41	25.0
-29	29.38	53.3	23.9
-28	30.38	53.3	22.9
-27	31.38	53.3	21.9
-26	32.38	53.32	20.9
-25	33.38	53.31	19.9
-24	34.38	53.33	19.0
-23	35.38	53.3	17.9
-22	36.38	53.3	16.9
-21	37.38	53.34	16.0
-20	38.38	53.32	14.9


Green: AGC Level

Yellow: AGC Level + 3

Orange: AGC Level + 14 (Full Input Power)

AGC THRESHOLD

Test Data: AGC Measurement Plot



Result:

The EUT passes signals below AGC with ~ 1.0 dB of loss + / - 0.2 dB.

The EUT maintains the output level above AGC at ~ 46.50 + / - 0.5 dB.

The EUT activates AGC at 22.445 dBm*.

***Note:** This behavior was found to be frequency dependent. Please see Out Of Band Rejection section for details.

OUT OF BAND REJECTION

Rule Part No.: KDB 935210 s.4.3, FCC Pt. 90.219(a), FCC Pt. 90.219(d)(7)

(a) *Definitions.* The definitions in this paragraph apply only to the rules in this section.

Class A signal booster. A signal booster designed to retransmit signals on one or more specific channels. A signal booster is deemed to be a Class A signal booster if none of its passbands exceed 75 kHz.

Class B signal booster. A signal booster designed to retransmit any signals within a wide frequency band. A signal booster is deemed to be a Class B signal booster if it has a passband that exceeds 75 kHz.

Requirements:


(7) Signal booster passbands are limited to the service band or bands for which the operator is authorized. In general, signal boosters should utilize the minimum passband that is sufficient to accomplish the purpose. Except for distributed antenna systems (DAS) installed in buildings, the passband of a Class B booster should not encompass both commercial services (such as ESMR and Cellular Radiotelephone) and part 90 Land Mobile and Public Safety Services.

Test Procedure: KDB 935210 s.4.3

Adjust the internal gain control of the EUT to the maximum gain for which equipment certification is sought.


- a) Connect a signal generator to the input of the EUT.
- b) Configure a swept CW signal with the following parameters:
 - 1) Frequency range = $\pm 250\%$ of the manufacturer's specified pass band.
 - 2) The CW amplitude shall be 3 dB below the AGC threshold (see 4.2), and shall not activate the AGC threshold throughout the test.
 - 3) Dwell time = approximately 10 ms.
 - 4) Frequency step = 50 kHz.
- c) Connect a spectrum analyzer to the output of the EUT using appropriate attenuation.
- d) Set the RBW of the spectrum analyzer to between 1 % and 5 % of the manufacturer's rated passband, and VBW = $3 \times$ RBW.
- e) Set the detector to Peak and the trace to Max-Hold.
- f) After the trace is completely filled, place a marker at the peak amplitude, which is designated as f_0 , and with two additional markers (use the marker-delta method) at the 20 dB bandwidth (i.e., at the points where the level has fallen by 20 dB).
- g) Capture the frequency response plot for inclusion in the test report.

Test Setup Block Diagram: KDB 935210 s.4.3



OUT OF BAND REJECTION

Test Data: Out of Band Rejection, Operational Band AGC




Date: 1.JAN.1997 05:10:56

OPERATING FREQUENCY RANGE = 450 - 470 MHz

Note: The operating frequency range is limited to the certified licensed PLMRS/PSRS 450 – 470 MHz equipment which will be used in conjunction with this amplifier.

OUT OF BAND REJECTION

Test Data: Out of Band Rejection, Operational Band AGC-3



Date: 1.JAN.1997 05:16:22

OPERATING FREQUENCY RANGE = 450 - 470 MHz

Note: The operating frequency range is limited to the certified licensed PLMRS/PSRS 450 – 470 MHz equipment which will be used in conjunction with this amplifier.

INPUT VS OUTPUT COMPARISON

Rule Part No.: KDB 935210 s.4.4, FCC Pt. 2.1049(h), FCC Pt. 90.219(e)(4)(ii),
FCC Pt. 90.219(e)(4)(iii), FCC Pt. 90.210(c)

Compliance with the emission mask of the EUT output shall be measured for the public safety service signal types as specified in 4.1.

Refer to the applicable regulatory requirements (e.g., Section 90.210) for emission mask specifications.

Requirements:

(e) *Device Specifications.* In addition to the general rules for equipment certification in §90.203(a)(2) and part 2, subpart J of this chapter, a signal booster must also meet the rules in this paragraph.

(4) A signal booster must be designed such that all signals that it retransmits meet the following requirements:

(ii) There is no change in the occupied bandwidth of the retransmitted signals.

(iii) The retransmitted signals continue to meet the unwanted emissions limits of §90.210 applicable to the corresponding received signals (assuming that these received signals meet the applicable unwanted emissions limits by a reasonable margin).

Frequency Band (MHz)	Mask for equipment with audio low pass filter			Mask for equipment without audio low pass filter		
	6.25 kHz	12.5 kHz	25 kHz	6.25 kHz	12.5 kHz	25 kHz
421 - 512	E, 6 kHz ABW	D, 11.25 kHz ABW	B, 20 kHz ABW	E, 6 kHz ABW	D, 11.25 kHz ABW	C, 20 kHz ABW

The frequencies for Input Vs Output shall be as follows:


Test Frequency	Mask Band	Mask	Operating Band	Signal(s)
451 MHz	421 – 512 MHz	Mask B or C	450 – 470 MHz	25kHz
451 MHz	421 – 512 MHz	Mask D	450 – 470 MHz	12.5kHz
451 MHz	421 – 512 MHz	Mask E	450 – 470 MHz	6.25kHz
460 MHz	421 – 512 MHz	Mask B or C	450 – 470 MHz	25kHz
460 MHz	421 – 512 MHz	Mask D	450 – 470 MHz	12.5kHz
460 MHz	421 – 512 MHz	Mask E	450 – 470 MHz	6.25kHz
469 MHz	421 – 512 MHz	Mask B or C	450 – 470 MHz	25kHz
469 MHz	421 – 512 MHz	Mask D	450 – 470 MHz	12.5kHz
469 MHz	421 – 512 MHz	Mask E	450 – 470 MHz	6.25kHz

INPUT VS OUTPUT COMPARISON

Test Procedure: KDB 935210 s.4.4

- a) Connect a signal generator to the input of the EUT.
- b) Configure the signal generator to transmit the appropriate test signal associated with the public safety emission designation (see Table 1).
- c) Configure the signal level to be just below the AGC threshold (see results from 4.2).
- d) Connect a spectrum analyzer to the output of the EUT using appropriate attenuation as necessary.
- e) Set the spectrum analyzer center frequency to the nominal EUT channel center frequency. The span range for the spectrum analyzer shall be between 2 times to 5 times the EBW (or OBW).
- f) The nominal RBW shall be 300 Hz for 16K0F3E, and 100 Hz for all other emissions types.
- g) Set the reference level of the spectrum analyzer to accommodate the maximum input amplitude level, i.e., the level at f_0 per 4.2.
- h) Set spectrum analyzer detection mode to peak, and trace mode to max hold.
- i) Allow the trace to fully stabilize.
- j) Confirm that the signal is contained within the appropriate emissions mask.
- k) Use the marker function to determine the maximum emission level and record the associated frequency as f_0 .
- l) Capture the emissions mask plot for inclusion in the test report (output signal spectra).
- m) Measure the EUT input signal power (signal generator output signal) directly from the signal generator using power measurement guidance provided in KDB Publication 971168 [R8] (input signal spectra).
- n) Compare the spectral plot of the output signal (determined in step k), to the input signal (determined in step l) to affirm they are similar (in passband and rolloff characteristic features and relative spectral locations).
- o) Repeat steps d) to n) with the input signal amplitude set 3 dB above the AGC threshold.
- p) Repeat steps b) to o) for all authorized operational bands and emissions types (see applicable regulatory specifications, e.g., Section 90.210).
- q) Include all accumulated spectral plots depicting EUT input signal and EUT output signal in the test report, and note any observed dissimilarities.

Test Setup Block Diagram: KDB 935210 s.4.4



INPUT VS OUTPUT COMPARISON

Emission Mask Calculation: FCC Pt. 90.210

Calculation	Limit (dBc)	dBc	dBm
#1 (Mask A, B, C, G, H)	$43 + 10 * \text{Log}(P)$	67.00	-13.00
#2 (Mask C)	$83 * \text{Log}(5 / 5)$	0.00	54.00
	$83 * \text{Log}(10 / 5)$	24.99	29.01
	Min dBc of: 50 or $29 * \text{Log}(10^2 / 11)$	27.80	26.20
	Min dBc of: 50 or $29 * \text{Log}((250\% \text{ ABW})^2 / 11)$	39.04	14.96
#3 (Mask D)	$7.27(5.625 - 2.88)$	19.96	34.04
	$7.27(12.5 - 2.88)$	69.94	-15.94
#4 (Mask E)	Min dBc of: 65 or $55 + 10 * \text{Log}(P)$ or $30 + 16.67(3-3)$	30.00	24.00
	Min dBc of: 65 or $55 + 10 * \text{Log}(P)$ or $30 + 16.67(4.6-3)$	56.67	-2.67
	Min dBc of: 65 or $55 + 10 * \text{Log}(P)$	65.00	-11.00

INPUT VS OUTPUT COMPARISON


Emission Mask Calculation: FCC Pt. 90.210(c)

MASK B, 20 kHz Authorized BW			
Requirement	f_d (kHz)	Level (dBc)	Level (dBm)
$\geq 250\%$ of ABW, see #1	≤ -50	67.00	-13.00
-100% to -250% of ABW, ≥ 35 dBc	-50	35.00	19.00
	-20		
-50% to -100% of ABW, ≥ 25 dBc	-20	25.00	29.00
	-10		
(Fundamental)	0	0.00	54.00
+ 50% to 100% of ABW, ≥ 25 dBc	+ 10	25.00	29.00
	+ 20		
+ 100% to 250% of ABW, ≥ 35 dBc	+ 20	35.00	19.00
	+ 50		
$\geq 250\%$ of ABW, see #1	$\geq + 50$	67.00	-13.00
MASK C, 20 kHz Authorized BW			
Requirement	f_d (kHz)	Level (dBc)	Level (dBm)
$\geq 250\%$ of ABW, see #1	≤ -50	67.00	-13.00
-10 kHz to -250% of ABW, see #2	-50	27.80	14.96
	-10	24.99	26.20
-5 kHz to -10 kHz, see #2	-10	24.99	29.01
	-5	0.00	54.00
(Fundamental)	0	0	
+5 kHz to +10 kHz, see #2	+ 5	0.00	
	+ 10	24.99	29.01
+10 kHz to +250% of ABW, see #2	+ 10	24.99	26.20
	+ 50	27.80	14.96
$\geq 250\%$ of ABW, see #1	$\geq + 50$	67.00	-13.00
MASK D, 11.25/20 kHz ABW			
Requirement	f_d (kHz)	Level (dBc)	Level (dBm)
≤ -12.5 kHz, see #3	≤ -12.5	67.00	-13.00
- 5.625 kHz to -12.5 kHz, see #3	-12.5	69.94	-15.94
	-5.625	19.96	34.04
-5.625 kHz > fundamental < +5.625 kHz, 0 dBc	-5.625	0.00	54.00
	0		
	+ 5.625		
+ 5.625 kHz to +12.5 kHz, see #3	+ 5.625	19.96	34.04
	+ 12.5	69.94	-15.94
$\geq +12.5$ kHz, see #3	$\geq + 12.5$	67.00	-13.00
MASK E, 6 kHz ABW			
Requirement	f_d (kHz)	Level (dBc)	Level (dBm)
≤ -4.6 kHz, see #4	≤ -4.6	65.00	-11.00
- 3 kHz to -4.6 kHz, see #4	-4.6	56.67	-2.67
	-3	30.00	24.00
-3 kHz > fundamental < +3 kHz, 0 dBc	-3	0.00	54.00
	0		
	+ 3		
+ 3 kHz to +4.6 kHz, see #4	+ 3	30.00	24.00
	+ 4.6	56.67	-2.67
$\geq +4.6$ kHz, see #4	$\geq + 4.6$	65.00	-11.00

INPUT VS OUTPUT COMPARISON

451 MHz

Test Data: 4K00F3E Output Signal, @ AGC




Date: 1.JAN.1997 03:50:19

RESULT: AGC Output Signal 99 % OBW = 4.2 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 4K00F3E Output Signal, @ AGC +3 dBm



Date: 1.JAN.1997 03:48:20


RESULT: AGC+3 Output Signal 99 % OBW = 4.2 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1E/F1D Output Signal, @ AGC



Ref Lvl 53.8 dBm
 Marker 1 [T1] -31.88 dBm
 451.06000000 MHz
 RBW 100 Hz
 VBW 5 kHz
 SWT 60 s
 RF Att 40 dB
 Unit dBm




Date: 1.JAN.1997 04:34:27

RESULT: AGC Output Signal 99 % OBW = 7.69kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1E/F1D Output Signal, @ AGC +3 dBm




Date: 1.JAN.1997 04:32:24

RESULT: AGC+3 Output Signal 99 % OBW = 7.45 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1W Output Signal, @ AGC




Date: 1.JAN.1997 04:27:33

RESULT: AGC Output Signal 99 % OBW = 7.69 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1W Output Signal, @ AGC +3 dBm




Date: 1.JAN.1997 04:29:37

RESULT: AGC+3 Output Signal 99 % OBW = 7.69 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 11K3F3E Output Signal, @ AGC




Date: 1.JAN.1997 03:54:43

RESULT: AGC Output Signal 99 % OBW = 6.49 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 11K3F3E Output Signal, @ AGC +3 dBm




Date: 1.JAN.1997 03:57:38

RESULT: AGC+3 Output Signal 99 % OBW = 6.49 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 16K0F3E Output Signal, @ AGC




Date: 1.JAN.1997 04:36:24

RESULT: AGC Output Signal 99 % OBW = 12.42 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 16K0F3E Output Signal, @ AGC +3 dBm




Date: 1.JAN.1997 04:36:55

RESULT: AGC+3 Output Signal 99 % OBW = 12.42 kHz

INPUT VS OUTPUT COMPARISON

460 MHz

Test Data: 4K00F3E Output Signal, @ AGC




Date: 1.JAN.1997 03:43:38

RESULT: AGC Output Signal 99 % OBW = 4.2 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 4K00F3E Output Signal, @ AGC +3 dBm




Date: 1.JAN.1997 03:44:47

RESULT: AGC+3 Output Signal 99 % OBW = 4.2 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1E/F1D Output Signal, @ AGC




Date: 1.JAN.1997 04:17:01

RESULT: AGC Output Signal 99 % OBW = 7.45 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1E/F1D Output Signal, @ AGC +3 dBm



Date: 1.JAN.1997 04:19:37


RESULT: AGC+3 Output Signal 99 % OBW = 7.69 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1W Output Signal, @ AGC



Ref Lvl 53.8 dBm
 Marker 1 [T1] -31.37 dBm
 460.06000000 MHz
 RBW 100 Hz
 VBW 5 kHz
 SWT 60 s
 RF Att 40 dB
 Unit dBm




Date: 1.JAN.1997 04:25:47

RESULT: AGC Output Signal 99 % OBW = 7.69 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1W Output Signal, @ AGC +3 dBm


 Ref Lvl 53.8 dBm
 Marker 1 [T1] -30.14 dBm
 460.06000000 MHz
 RBW 100 Hz
 VBW 5 kHz
 SWT 60 s
 RF Att 40 dB
 Unit dBm




Date: 1.JAN.1997 04:23:17

RESULT: AGC+3 Output Signal 99 % OBW = 7.69 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 11K3F3E Output Signal, @ AGC




Date: 1.JAN.1997 04:01:27

RESULT: AGC Output Signal 99 % OBW = 7.21 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 11K3F3E Output Signal, @ AGC +3 dBm




Date: 1.JAN.1997 03:59:47

RESULT: AGC+3 Output Signal 99 % OBW = 7.21 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 16K0F3E Output Signal, @ AGC



Date: 1.JAN.1997 04:37:53


RESULT: AGC Output Signal 99 % OBW = 12.42 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 16K0F3E Output Signal, @ AGC +3 dBm



Ref Lvl 53.8 dBm
 Marker 1 [T1] -29.66 dBm
 459.95000000 MHz
 RBW 300 Hz
 VBW 5 kHz
 SWT 5.6 s
 RF Att 40 dB
 Unit dBm




Date: 1.JAN.1997 04:37:25

RESULT: AGC+3 Output Signal 99 % OBW = 12.42 kHz

INPUT VS OUTPUT COMPARISON

469 MHz

Test Data: 4K00F3E Output Signal, @ AGC




Date: 1.JAN.1997 03:41:08

RESULT: AGC Output Signal 99 % OBW = 4.2 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 4K00F3E Output Signal, @ AGC +3 dBm




Date: 1.JAN.1997 03:46:22

RESULT: AGC+3 Output Signal 99 % OBW = 4.2 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1E/F1D Output Signal, @ AGC




Date: 1.JAN.1997 04:15:20

RESULT: AGC Output Signal 99 % OBW = 7.46 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1E/F1D Output Signal, @ AGC +3 dBm



Date: 1.JAN.1997 04:13:53


RESULT: AGC+3 Output Signal 99 % OBW = 7.69 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1W Output Signal, @ AGC



Marker 1 [T1] RBW 100 Hz RF Att 40 dB
 Ref Lvl -30.80 dBm VBW 5 kHz
 53.8 dBm 468.94000000 MHz SWT 60 s Unit dBm




Date: 1.JAN.1997 04:08:29

RESULT: AGC Output Signal 99 % OBW = 7.69 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 8K10F1W Output Signal, @ AGC +3 dBm



Date: 1.JAN.1997 04:12:23


RESULT: AGC+3 Output Signal 99 % OBW = 7.69 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 11K3F3E Output Signal, @ AGC



Marker 1 [T1] RBW 100 Hz RF Att 40 dB
 Ref Lvl -28.48 dBm VBW 5 kHz
 53.8 dBm 468.94000000 MHz SWT 60 s Unit dBm




Date: 1.JAN.1997 04:03:09

RESULT: AGC Output Signal 99 % OBW = 7.21 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 11K3F3E Output Signal, @ AGC +3 dBm




Date: 1.JAN.1997 04:05:03

RESULT: AGC+3 Output Signal 99 % OBW = 6.97 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 16K0F3E Output Signal, @ AGC




Date: 1.JAN.1997 04:38:25

RESULT: AGC Output Signal 99 % OBW = 12.42 kHz

INPUT VS OUTPUT COMPARISON

Test Data: 16K0F3E Output Signal, @ AGC +3 dBm



Date: 1.JAN.1997 04:38:51

RESULT: AGC+3 Output Signal 99 % OBW = 12.42 kHz

RF POWER OUTPUT

Rule Part No.: KDB 935210 s.4.5, 4.5.5, FCC Pt. 2.1046(a), FCC Pt. 2.1033(c)(8), FCC Pt. 90.219(d)(3), FCC Pt. 90.219(e)(1), FCC Pt. 90.219(e)(4)(iii)

Requirements:

(d) *Deployment rules.* Deployment of signal boosters must be carried out in accordance with the rules in this paragraph.

(3) Signal boosters must be deployed such that the radiated power of the each retransmitted channel, on the forward link and on the reverse link, does not exceed 5 Watts effective radiated power (ERP).

(e) *Device Specifications.* In addition to the general rules for equipment certification in §90.203(a)(2) and part 2, subpart J of this chapter, a signal booster must also meet the rules in this paragraph.

(1) The output power capability of a signal booster must be designed for deployments providing a radiated power not exceeding 5 Watts ERP for each retransmitted channel.

Test Procedure: KDB 935210 s.4.5, & 4.5.3, TIA 603-E

Adjust the internal gain control of the EUT to the maximum gain for which the equipment certification is being sought. Any EUT attenuation settings shall be set to their minimum value.

Input power levels (uplink and downlink) should be set to maximum input ratings, while confirming that the device is not capable of operating in saturation (non-linear mode) at the rated input levels, including during the performance of the input/output power measurements.

4.5.3 Power measurement Method 1: using a spectrum or signal analyzer

- a) Set the frequency span to at least 1 MHz.
- b) Set RBW = 100 kHz.
- c) Set VBW $\geq 3 \times$ RBW.
- d) Set the detector to PEAK, and trace mode to MAX HOLD.
- e) Place a marker on the peak of the signal, and record the value as the maximum power.
- f) Repeat step e) but with the EUT in place.
- g) EUT gain may be calculated as described in 4.5.5.


NOTE—Sections 90.219 and 2.1033(c) do not require gain test data; inclusion of industrial booster gain test data in test reports submitted for FCC equipment authorization is optional.

After the input and output power levels have been measured as described in the preceding subclauses, the gain of the EUT can be determined from:

$$\text{Gain (dB)} = \text{output power (dBm)} - \text{input power (dBm)}.$$

Report the gain for each authorized operating frequency band, and each test signal stimulus.

Test Setup Block Diagram: KDB 935210 s.4.5



RF POWER OUTPUT

Test Data: 400 Band Measurement Table

Frequency	AGC Level	Input (dBm)	Output (dBm)	Antenna Gain (dBi)	Cable Loss (dB)	Gain (dB)	Output ERP (W)	Limit ERP (W)	Margin (W)
451.0	AGC	28.22	53.42	0.00	0.00	25.2	219.79	5.00	-214.79
451.0	AGC +3	31.15	53.41	0.00	0.00	22.3	219.28	5.00	-214.28
451.0	Saturation	37.97	53.42	0.00	0.00	15.5	219.79	5.00	-214.79
460.0	AGC	28.22	53.68	0.00	0.00	25.5	233.35	5.00	-228.35
460.0	AGC +3	31.15	53.66	0.00	0.00	22.5	232.27	5.00	-227.27
460.0	Saturation	37.97	53.66	0.00	0.00	15.7	232.27	5.00	-227.27
469.00	AGC	28.22	53.81	0.00	0.00	25.6	240.44	5.00	-235.44
469.00	AGC +3	31.15	53.81	0.00	0.00	22.7	240.44	5.00	-235.44
469.00	Saturation	37.97	53.81	0.00	0.00	15.8	240.44	5.00	-235.44

Maximum Power Output: 53.81 dBm (240.44 W)

POWER TO FINAL AMPLIFIER


Rule Part No.: FCC Pt. 2.1033(c)(8)

Requirements:

(c) Applications for equipment other than that operating under parts 15, 11 and 18 of this chapter shall be accompanied by a technical report containing the following information:

(8) The dc voltages applied to and dc currents into the several elements of the final radio frequency amplifying device for normal operation over the power range.

Test Setup Block Diagram:



Test Data: Power to Final Amplifier Calculation

INPUT POWER: (120 VAC) (10 A) = **1200 Watts Maximum**

NOISE FIGURE

Rule Part No.: KDB 935210 s.4.6, FCC Pt. 90.219(e)(2)

Section 90.219(e)(2) limits the noise figure of a signal booster to ≤ 9 dB in either direction. The following discussion provides guidance for demonstrating compliance with this requirement.

Several widely recognized methods for performing noise figure measurements are available. Some require the use of specialized equipment, such as a noise figure analyzer and/or an excess noise ratio (ENR) calibrated noise source, while others involve the use of conventional measurement instrumentation such as a spectrum analyzer. Methods that require use of a noise figure analyzer are generally accepted as producing the most accurate results, and are considered to be the reference method within this document, while others are considered to be acceptable alternative methods. Consult the relevant instrumentation application notes for detailed guidance regarding the selection and application of an appropriate methodology for performing noise figure measurements. Note also that noise figure measurements require that any AGC circuitry be disabled over the duration of the measurement.

Requirements:

(e) *Device Specifications.* In addition to the general rules for equipment certification in §90.203(a)(2) and part 2, subpart J of this chapter, a signal booster must also meet the rules in this paragraph.


(2) The noise figure of a signal booster must not exceed 9 dB in either direction.

Test Procedure: FCC KDB 935210 S. 4.6, ISSED RSS-131 S. 6.4 - NOISE FIGURE, per "Noise Figure Measurement Accuracy: The Y-Factor Method" (by Keysight Technologies)

Setup using an RBW of 10 kHz, VBW $\geq 3 \times$ RBW, Span $> 2 \times$ Passband, Max Hold, Peak Detector. "Noise Source off" and "Noise Source on" traces were taken.

Note: EUT's AGC method(s) and/or squelch function should be disabled for this test.

Test Setup Block Diagram:



NOISE FIGURE

450 – 470 MHz Band Noise Figure

Test Data: 450 MHz Noise Calculation

UHF BAND	
FCC KDB 935210 S. 4.6, ISSED RSS-131 S. 6.4 - NOISE FIGURE	
Measurement Freq. (MHz)	450
Noise Source ENR (dB)	15.1072
Noise Source T_s^{OFF} , T_0 (K)	290
Noise Source T_s^{ON} (K)	9689.8348
Noise Source Cal N_2^{off} (dB)	-124.07
Noise Source Cal N_2^{off} (pW)	0.00039
Noise Source Cal N_2^{on} (dB)	-108.23
Noise Source Cal N_2^{on} (pW)	0.01503
Calibration Ratio Y_2	38.3707
Calibration T_2	-38.4706
Noise + EUT N_{12}^{off} (dB)	-127.42
Noise + EUT N_{12}^{off} (pW)	0.00
Noise + EUT N_{12}^{on} (dB)	-117.01
Noise + EUT N_{12}^{on} (pW)	0.00
Noise + EUT Ratio Y_{12}	10.9901
Noise + EUT T_{12}	650.9189
Gain (Ratio)	0.1236
Gain (dB)	-9.0796
2nd Stage Correction T_1	962.157031863277
Noise Factor F	4.31778
Noise Figure (dB)	6.35
Limit (dB)	9.00
Margin (dB)	2.65

INTERMODULATION SPURIOUS EMISSIONS


Test Procedure: KDB 935210 s.4.7.2, TIA 603-E

Intermodulation products shall be measured using two CW signals with all available channel spacings (e.g., 12.5 kHz and 6.25 kHz) with the center between these channels being equal to the center frequency f_0 as determined from 4.4.

NOTE—Intermodulation-product spurious emission measurements are not required for single-channel boosters that cannot accommodate two simultaneous signals within the passband.

- a) Connect a signal generator to the input of the EUT.
If the signal generator is not capable of producing two independent modulated carriers simultaneously, then two discrete signal generators can be connected, with an appropriate combining network to support the two-signal test.
- b) Configure the two signal generators to produce CW on frequencies spaced consistent with 4.7.1, with amplitude levels set to just below the AGC threshold (see 4.2).
- c) Connect a spectrum analyzer to the EUT output.
- d) Set the span to 100 kHz.
- e) Set RBW = 300 Hz with VBW $\geq 3 \times$ RBW.
- f) Set the detector to power averaging (rms).
- g) Place a marker on highest intermodulation product amplitude.
- h) Capture the plot for inclusion in the test report.
- i) Repeat steps c) to h) with the composite input power level set to 3 dB above the AGC threshold.
- j) Repeat steps b) to i) for all operational bands.

Test Setup Block Diagram: KDB 935210 s.4.7.2



Test Data: n/a

Note: The EUT will be used exclusively by a single transmitter, and as such is considered a single channel booster which will not amplify multiple signals.

SPURIOUS EMISSIONS AT ANTENNA TERMINALS

Rule Part No.: KDB 935210 s.4.7.3, FCC Part 2.1051(a), FCC Pt. 90.219(e)(3)

Refer to the applicable rule part(s) for specified limits on unwanted (out-of-band/out-of-block and spurious) emissions (e.g., Section 90.210).

Requirements:

(e) *Device Specifications.* In addition to the general rules for equipment certification in §90.203(a)(2) and part 2, subpart J of this chapter, a signal booster must also meet the rules in this paragraph.


(3) Spurious emissions from a signal booster must not exceed -13 dBm within any 100 kHz measurement bandwidth.

Test Procedure: KDB 935210 s.4.7.3, TIA 603-E

Spurious emissions shall be measured using a single test signal sequentially tuned to the low, middle, and high channels or frequencies within each authorized frequency band of operation.

- a) Connect a signal generator to the input of the EUT.
- b) Configure the signal generator to produce a CW signal.
- c) Set the frequency of the CW signal to the center channel of the EUT passband.
- d) Set the output power level so that the resultant signal is just below the AGC threshold (see 4.2).
- e) Connect a spectrum analyzer to the output of the EUT, using appropriate attenuation as necessary.
- f) Set the RBW = 100 kHz. (i.e., for 30 MHz to 1 GHz PLMRS and/or PSRS booster devices)
- g) Set the VBW = $3 \times \text{RBW}$.
- h) Set the Sweep time = auto-couple.
- i) Set the detector to PEAK.
- j) Set the spectrum analyzer start frequency to 30 MHz (or the lowest radio frequency signal generated in the EUT, without going below 9 kHz if the EUT has additional internal clock frequencies), and the stop frequency to 10 times the highest allowable frequency of the EUT passband.
- k) Select MAX HOLD, and use the marker peak function to find the highest emission(s) outside the passband. (This could be either at a frequency lesser or greater than the passband frequencies.)
- l) Capture a plot for inclusion in the test report.
- m) Repeat steps c) to l) for each authorized frequency band/block of operation.


Test Setup Block Diagram: KDB 935210 s.4.7.3



Note 1: The standard method was deviated from during testing. Instead of four discrete frequencies, the entire passband was swept from 406 – 421 MHz to generate all possible spurious emissions.

SPURIOUS EMISSIONS AT ANTENNA TERMINALS

Test Data: Conducted Spurious Emissions Below 1 GHz




Date: 1.JAN.1997 05:22:53

Frequency	Measured Level (dBm)	Limit (dBm)	Margin
479.88	-18.76	-13	5.76
910.77	-20.19	-13	7.19

Note: F1 and F2 frequency lines indicate the operational band were the fundamental frequency was swept.

SPURIOUS EMISSIONS AT ANTENNA TERMINALS

Test Data: Conducted Spurious Emissions Above 1 GHz



Date: 1.JAN.1997 05:25:36

Frequency	Measured Level (dBm)	Limit (dBm)	Margin
1352.7	-18.65	-13	5.65

FREQUENCY STABILITY

Rule Part No.: KDB 935210 s.4.8, FCC Part 2.1055(a)(1), FCC Pt. 90.219(e)(4)(i)

Section 90.219(e)(4)(i) requires that a signal being retransmitted by an amplifier, repeater, or industrial booster meets the frequency stability requirements of Section 90.213. However, this requirement presumes that the EUT processes an input signal in ways that can influence the output signal frequency/frequencies; however, most signal boosters do not incorporate an oscillator). If the amplifier, booster, or repeater does not alter the input signal in any way, then a frequency stability test may not be required.

Requirements: FCC Part 2.1055(a)(1)

(a) The frequency stability shall be measured with variation of ambient temperature as follows:


(1) From -30° to $+50^{\circ}$ centigrade for all equipment except that specified in paragraphs (a) (2) and (3) of this section.

Test Procedure: KDB 935210 s.4.8, FCC Part 2.1055(b), TIA 603-E

When performing frequency stability measurements on these types of devices, the instability associated with the EUT must be isolated from any frequency instability associated with the measurement instrumentation. One method for realizing such isolation is to connect the reference clock input of the signal generator to the reference output of the frequency counter, to confirm that any frequency instability is associated with the EUT, and is not due to differences between the reference oscillators internal to the measurement instrumentation.

(b) Frequency measurements shall be made at the extremes of the specified temperature range and at intervals of not more than 10° centigrade through the range. A period of time sufficient to stabilize all of the components of the oscillator circuit at each temperature level shall be allowed prior to frequency measurement. The short term transient effects on the frequency of the transmitter due to keying (except for broadcast transmitters) and any heating element cycling normally occurring at each ambient temperature level also shall be shown. Only the portion or portions of the transmitter containing the frequency determining and stabilizing circuitry need be subjected to the temperature variation test.

Test Setup Block Diagram:



RESULT: Not Applicable to EUT.

FIELD STRENGTH OF SPURIOUS EMISSIONS

Rule Part No.: KDB 935210 s.4.9, FCC Part 2.1053(a), FCC Pt. 90.219(e)(3)

Refer to the applicable rule part(s) for specified limits on unwanted (out-of-band/out-of-block and spurious) emissions (e.g., Section 90.210).

Requirements:

(e) *Device Specifications.* In addition to the general rules for equipment certification in §90.203(a)(2) and part 2, subpart J of this chapter, a signal booster must also meet the rules in this paragraph.

(3) Spurious emissions from a signal booster must not exceed -13 dBm within any 100 kHz measurement bandwidth.


Test Procedure: KDB 935210 s.4.7.3, TIA 603-E

Spurious emissions shall be measured using a single test signal sequentially tuned to the low, middle, and high channels or frequencies within each authorized frequency band of operation.


- a) Connect a signal generator to the input of the EUT.
- b) Configure the signal generator to produce a CW signal.
- c) Set the frequency of the CW signal to the center channel of the EUT passband.
- d) Set the output power level so that the resultant signal is just below the AGC threshold (see 4.2).
- e) Connect a spectrum analyzer to the output of the EUT, using appropriate attenuation as necessary.
- f) Set the RBW = 100 kHz. (i.e., for 30 MHz to 1 GHz PLMRS and/or PSRS booster devices)
- g) Set the VBW = $3 \times$ RBW.
- h) Set the Sweep time = auto-couple.
- i) Set the detector to PEAK.
- j) Set the spectrum analyzer start frequency to 30 MHz (or the lowest radio frequency signal generated in the EUT, without going below 9 kHz if the EUT has additional internal clock frequencies), and the stop frequency to 10 times the highest allowable frequency of the EUT passband.
- k) Select MAX HOLD, and use the marker peak function to find the highest emission(s) outside the passband. (This could be either at a frequency lesser or greater than the passband frequencies.)
- l) Capture a plot for inclusion in the test report.
- m) Repeat steps c) to l) for each authorized frequency band/block of operation.

FIELD STRENGTH OF SPURIOUS EMISSIONS

Test Site Setup:



EUT Orientation(s):



Note: The tabulated data shows the results of the radiated field strength emissions test. The spectrum was scanned from the lowest frequency generated internally to at least the tenth harmonic of the fundamental. This test was conducted in accordance with the standard listed above using the substitution method. Measurements were made at the test site of TIMCO ENGINEERING, INC. located at 849 NW State Road 45, Newberry, FL 32669. The measurements below represent the worst case of all the frequencies tested.

Note: Six (6) or more of the highest emissions of each worst-case operational mode of the EUT are represented below. Emissions 20 dB below the limit were not required to be reported.

Note: The EUT was supplied with the worst-case in-band input signals (determined in Conducted Spurious Emissions) at Maximum Input Power (4W) of the EUT.

FIELD STRENGTH OF SPURIOUS EMISSIONS

451 MHz Radiated Spurious Emissions

Power Output		Limit								
dBm	Watts	dBc	dBm							
53.81	240.44	66.81	-13.00							
Tuned Frequency (MHz)	Emission Frequency (MHz)	Meter Reading (dBμV)	Antenna Polarity	Coax Loss (dB)	Correction Factor (dB/m)	Field Strength (dBμV/m)	Distance (m)	Field Strength (dBμV/m)	ERP (dBm)	Margin (dB)
451.00	902.00	39.74	V	3.54	21.90	65.18	3.000	65.182	-32.195	19.20
451.00	902.00	34.69	H	3.54	21.90	60.13	3.000	60.132	-37.245	24.25
451.00	1353.00	12.10	V	3.97	28.18	44.25	3.000	44.247	-53.131	40.13
451.00	1353.00	12.39	H	3.97	28.18	44.54	3.000	44.537	-52.841	39.84
451.00	1804.00	14.15	H	4.70	28.33	47.18	3.000	47.178	-50.199	37.20
451.00	1804.00	13.90	V	4.70	28.33	46.93	3.000	46.928	-50.449	37.45
451.00	2255.00	13.79	V	5.21	31.11	50.11	3.000	50.113	-47.264	34.26
451.00	2255.00	11.24	H	5.21	31.11	47.56	3.000	47.563	-49.814	36.81
451.00	2706.00	12.03	H	5.62	31.85	49.50	3.000	49.500	-47.877	34.88
451.00	2706.00	11.90	V	5.62	31.85	49.37	3.000	49.370	-48.007	35.01
451.00	3157.00	12.64	V	6.17	32.35	51.16	3.000	51.161	-46.216	33.22
451.00	3157.00	10.97	H	6.17	32.35	49.49	3.000	49.491	-47.886	34.89
451.00	3608.00	12.13	H	6.65	32.68	51.46	3.000	51.457	-45.920	32.92
451.00	3608.00	12.66	V	6.65	32.68	51.99	3.000	51.987	-45.390	32.39
451.00	4059.00	13.02	V	6.58	33.20	52.80	3.000	52.795	-44.582	31.58
451.00	4059.00	10.13	H	6.58	33.20	49.91	3.000	49.905	-47.472	34.47
451.00	4510.00	9.66	H	7.17	33.38	50.21	3.000	50.209	-47.169	34.17
451.00	4510.00	10.66	V	7.17	33.38	51.21	3.000	51.209	-46.169	33.17

460 MHz Radiated Spurious Emissions

Power Output		Limit								
dBm	Watts	dBc	dBm							
53.81	240.44	66.81	-13.00							
Tuned Frequency (MHz)	Emission Frequency (MHz)	Meter Reading (dBμV)	Antenna Polarity	Coax Loss (dB)	Correction Factor (dB/m)	Field Strength (dBμV/m)	Distance (m)	Field Strength (dBμV/m)	ERP (dBm)	Margin (dB)
460.00	902.00	39.04	H	3.58	22.30	64.92	3.000	64.920	-32.457	19.46
460.00	902.00	32.11	V	3.58	22.30	57.99	3.000	57.990	-39.387	26.39
460.00	1353.00	11.55	V	3.99	28.34	43.88	3.000	43.879	-53.499	40.50
460.00	1353.00	10.66	H	3.99	28.34	42.99	3.000	42.989	-54.389	41.39
460.00	1804.00	11.79	H	4.73	28.62	45.14	3.000	45.140	-52.237	39.24
460.00	1804.00	11.64	V	4.73	28.62	44.99	3.000	44.990	-52.387	39.39
460.00	2255.00	10.94	V	5.26	31.00	47.20	3.000	47.204	-50.174	37.17
460.00	2255.00	12.48	V	5.62	32.09	50.19	3.000	50.190	-47.197	34.19
460.00	2706.00	11.30	V	6.22	32.23	49.75	3.000	49.745	-47.632	34.63
460.00	2706.00	10.50	H	6.22	32.23	48.95	3.000	48.945	-48.432	35.43
460.00	3157.00	11.23	H	6.68	32.62	50.53	3.000	50.535	-46.843	33.84
460.00	3157.00	12.80	V	6.68	32.62	52.10	3.000	52.105	-45.273	32.27
460.00	3608.00	9.76	V	6.50	33.17	49.43	3.000	49.430	-47.948	34.95
460.00	3608.00	10.44	H	6.50	33.17	50.11	3.000	50.110	-47.268	34.27
460.00	4059.00	10.41	H	7.07	33.41	50.89	3.000	50.894	-46.483	33.48
460.00	4059.00	9.53	V	7.07	33.41	50.01	3.000	50.014	-47.363	34.36
460.00	4510.00	15.32	H	3.38	20.44	39.14	3.000	39.144	-58.233	45.23
460.00	4510.00	12.11	V	3.38	20.44	35.93	3.000	35.934	-61.443	48.44

FIELD STRENGTH OF SPURIOUS EMISSIONS

469 MHz Radiated Spurious Emissions

Power Output		Limit								
dBm	Watts	dBc	dBm							
53.81	240.44	66.81	-13.00							
Tuned Frequency (MHz)	Emission Frequency (MHz)	Meter Reading (dBμV)	Antenna Polarity	Coax Loss (dB)	Correction Factor (dB / m)	Field Strength (dBμV / m)	Distance (m)	Field Strength (dBμV / m)	ERP (dBm)	Margin (dB)
469.00	902.00	18.50	V	3.40	20.94	42.84	3.000	42.840	-54.537	41.54
469.00	902.00	16.85	H	3.40	20.94	41.19	3.000	41.190	-56.187	43.19
469.00	1353.00	14.75	H	3.45	22.10	40.30	3.000	40.300	-57.077	44.08
469.00	1353.00	15.50	V	3.45	22.10	41.05	3.000	41.050	-56.327	43.33
469.00	1804.00	33.62	V	3.59	22.60	59.81	3.000	59.808	-37.569	24.57
469.00	1804.00	25.69	H	3.59	22.60	51.88	3.000	51.878	-45.499	32.50
469.00	2255.00	12.59	V	4.02	28.47	45.08	3.000	45.084	-52.293	39.29
469.00	2255.00	11.53	H	4.02	28.47	44.02	3.000	44.024	-53.353	40.35
469.00	2706.00	13.52	H	4.76	28.88	47.16	3.000	47.162	-50.216	37.22
469.00	2706.00	11.18	V	4.76	28.88	44.82	3.000	44.822	-52.556	39.56
469.00	3157.00	11.80	V	5.31	31.04	48.15	3.000	48.154	-49.223	36.22
469.00	3157.00	10.17	H	5.31	31.04	46.52	3.000	46.524	-50.853	37.85
469.00	3608.00	13.35	H	5.66	32.41	51.42	3.000	51.415	-45.962	32.96
469.00	3608.00	11.63	V	5.66	32.41	49.70	3.000	49.695	-47.682	34.68
469.00	4059.00	11.36	H	6.26	32.31	49.93	3.000	49.932	-47.445	34.44
469.00	4059.00	12.29	V	6.26	32.31	50.86	3.000	50.862	-46.515	33.51
469.00	4510.00	11.38	V	6.72	32.64	50.74	3.000	50.740	-46.637	33.64
469.00	4510.00	11.21	H	6.72	32.64	50.57	3.000	50.570	-46.807	33.81

STATEMENT OF MEASUREMENT UNCERTAINTY

The data and results referenced in this document are true and accurate. The measurement uncertainty was calculated for all measurements listed in this test report according To CISPR 16-4 or ENTR 100-028 Specification for radio disturbance and immunity measuring apparatus and methods – Part 4: “Uncertainty in EMC Measurements” and is documented in the Timco Engineering, Inc. quality system according to DIN EN ISO/IEC 17025. Furthermore, component and process variability of devices similar to that tested may result in additional deviation. The manufacturer has the sole responsibility of continued compliance of the device.

Hereafter the best measurement capability for Timco Engineering, Inc. is reported:

Test Items	Measurement Uncertainty	Notes
RF Frequency Accuracy	± 49.5 Hz	(1)
RF Conducted Power	± 0.93 dB	(1)
Conducted spurious emission of transmitter valid up to 40GHz	± 1.86 dB	
Occupied Bandwidth	± 2.65 %	
Radiated RF Power	± 1.4 dB	
Rad Emissions Sub Meth up to 26.5GHz	± 2.14 dB	
Adjacent channel power	± 0.93 dB	(1)

Notes: (1) This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of $k=1.96$.

EMC EQUIPMENT LIST

Device	Manufacturer	Model	Serial Number	Cal/Char Date	Due Date
Antenna: Biconical 1057	Eaton	94455-1	1057	12/13/17	12/13/19
Antenna: Log-Periodic 1243	Eaton	96005	1243	04/20/18	04/20/20
Coaxial Cable - Chamber 3 cable set (backup)	Micro-Coax	Chamber 3 cable set (backup)	KMKM-0244-02 KMKM-0670-01 KFKF-0197-00	02/27/19	02/27/21
CHAMBER	Panashield	3M	N/A	03/12/19	03/12/21
Antenna: Double-Ridged Horn/ETS Horn 1	ETS-Lindgren	3117	00035923	01/30/17	01/30/20
Software: Field Strength Program	Timco	N/A	Version 4.10.7.0	N/A	N/A
EMI Test Receiver R & S ESU 40	Rohde & Schwarz	ESU 40	100320	08/28/18	08/28/20
Bore-sight Antenna Positioning Tower	Sunol Sciences	TLT2	N/A	N/A	N/A
Attenuator N 30dB 100W DC-6G	Pasternack	PE7214-30	#109	08/23/19	08/23/21
Coaxial Cable - BMBM-0061-01 RG400	Pasternack	PE3582LF-24	BMBM-0061-01	08/23/19	08/23/21
Coaxial Cable - BMBM-0061-02 RG400	Pasternack	PE3582LF-24	BMBM-0061-02	08/23/19	08/23/21
Coaxial Cable - BMBM-0122-01 RG400	Pasternack	PE3582LF-48	BMBM-0122-01	08/23/19	08/23/21
Coaxial Cable - BMBM-0122-02 RG400	Pasternack	PE3582LF-48	BMBM-0122-02	08/23/19	08/23/21
Coaxial Cable - BMBM-0183-01 RG400	Pasternack	PE3582LF-72	BMBM-0183-01	08/23/19	08/23/21
Coaxial Cable - BMBM-0183-02 RG400	Pasternack	PE3582LF-72	BMBM-0183-02	08/23/19	08/23/21
Terminator N 20W DC-18G	Narda	8205	#14	N/A	N/A
10 W Amplifier	Amplifier Research	10W1000B	23117	08/23/19	08/23/21
Signal Generator R & S SMU 200A	Rohde & Schwarz	SMU200A	103195	04/23/18	04/23/20
Signal Generator HP 8648C	HP	8648C	3537A01679	03/29/19	03/29/21

*EMI RECEIVER SOFTWARE VERSION

The receiver firmware used was version 4.43 Service Pack 3

END OF TEST REPORT