

8 CONDUCTED RF OUPUT POWER

8.1	WIFI Output Power
8.1.1	WIFI2.4G Output Power
8.1.2	WIFI5G Output Power
8.2	Bluetooth
8.2.1	Bluetooth Output Power
8.2.2	Bluetooth Duty Cycle

8.1 WIFI Output Power

8.1.1 WIFI2.4G Output Power

Test Mode	Modulation	Channel number	Frequency	AV power (dBm)	Tune-up (dBm)	SAR Test
2.4G	11b	1	2412	16.66	17.00	Yes
		6	2437	16.69	17.00	Yes
		11	2462	16.61	17.00	Yes
	11g	1	2412	16.81	17.00	No
		6	2437	16.57	17.00	No
		11	2462	16.46	17.00	No
	11n-HT20	1	2412	16.21	17.00	No
		6	2437	16.64	17.00	No
		11	2462	16.28	17.00	No
	11n-HT40	3	2422	15.67	17.00	No
		6	2437	16.87	17.00	No
		9	2452	16.65	17.00	No
	11ax-HT20	1	2412	15.98	17.00	No
		6	2437	16.64	17.00	No
		11	2462	16.53	17.00	No
	11ax-HT40	3	2422	15.82	17.00	No
		6	2437	16.59	17.00	No
		9	2452	16.83	17.00	No

Note: When multiple channel bandwidth configurations in a frequency band have the same maximum tune-up output power, the test configuration is determined by applying the following steps sequentially.

- (1) The largest channel bandwidth configuration is selected between the multiple configurations in a frequency band with the same maximum tune-up output power.
- (2) When multiple transmission modes (802.11b/g/n/ax) have the same maximum tune-up output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11b is chosen over 802.11g, and 802.11g chosen over 802.11n, and 802.11n chosen over 802.11ax.
- (3) According KDB 247228, when the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg, OFDM SAR test is not required.
Adjusted SAR = $0.698 * (50.12\text{mW}/50.12\text{mW}) = 0.698$ W/Kg, so 2.4G OFDM SAR test is not required.

8.1.2 WIFI5G Output Power

Test Mode	Modulation	Channel	Frequency	AV power (dBm)	Tune-up (dBm)	SAR Test
WIFI 5G Band1	11a	36	5180	12.58	13.00	No
		44	5220	12.21	13.00	No
		48	5240	12.11	13.00	No
	11n20	36	5180	12.16	13.00	No
		44	5220	12.48	13.00	No
		48	5240	12.42	13.00	No
	11n40	38	5190	12.38	13.00	No
		46	5230	12.41	13.00	No
	11ac20	36	5180	12.21	13.00	No
		44	5220	12.53	13.00	No
		48	5240	12.47	13.00	No
	11ac40	38	5190	12.37	13.00	No
		46	5230	12.53	13.00	No
	11ac80	42	5210	12.21	13.00	No
	11ax20	36	5180	12.51	13.00	No
		44	5220	12.63	13.00	No
		48	5240	12.63	13.00	No
	11ax40	38	5190	12.15	13.00	No
		46	5230	12.23	13.00	No
	11ax80	42	5210	12.18	13.00	No
WIFI 5G Band2	11a	52	5260	12.65	13.00	No
		60	5300	12.62	13.00	No
		64	5320	12.88	13.00	No
	11n20	52	5260	12.49	13.00	No
		60	5300	12.48	13.00	No
		64	5320	12.72	13.00	No
	11n40	54	5270	12.61	13.00	No
		62	5310	12.81	13.00	No
	11ac20	52	5260	12.54	13.00	No
		60	5300	12.53	13.00	No
		64	5320	12.74	13.00	No
	11ac40	54	5270	12.57	13.00	No
		62	5310	12.79	13.00	No
	11ac80	58	5290	12.40	13.00	Yes
	11ax20	52	5260	12.58	13.00	No
		60	5300	12.86	13.00	No
		64	5320	12.52	13.00	No
	11ax40	54	5270	12.81	13.00	No
		62	5310	12.61	13.00	No
	11ax80	58	5290	12.40	13.00	No

WIFI 5G Band3	11a	100	5500	13.01	13.50	No
		116	5580	13.26	13.50	No
		140	5700	13.39	13.50	No
	11n20	100	5500	13.36	13.50	No
		116	5580	13.12	13.50	No
		140	5700	13.29	13.50	No
	11n40	102	5510	13.02	13.50	No
		118	5590	13.22	13.50	No
		134	5670	13.36	13.50	No
	11ac20	100	5500	13.40	13.50	No
		116	5580	13.14	13.50	No
		140	5700	13.27	13.50	No
	11ac40	102	5510	13.06	13.50	No
		118	5590	13.27	13.50	No
		134	5670	13.35	13.50	No
	11ac80	106	5530	12.89	13.50	Yes
		122	5610	12.32	13.50	Yes
	11ax20	100	5500	13.18	13.50	No
		116	5580	13.36	13.50	No
		140	5700	13.03	13.50	No
	11ax40	102	5510	13.34	13.50	No
		118	5590	13.42	13.50	No
		134	5670	13.12	13.50	No
	11ax80	106	5530	12.95	13.50	No
		122	5610	13.12	13.50	No

WIFI 5G Band4	11a	149	5745	14.03	14.50	No
		157	5785	14.43	14.50	No
		165	5825	13.89	14.50	No
	11n20	149	5745	13.89	14.50	No
		157	5785	14.27	14.50	No
		165	5825	14.35	14.50	No
	11n40	151	5755	13.95	14.50	No
		159	5795	14.23	14.50	No
	11ac20	149	5745	13.89	14.50	No
		157	5785	14.30	14.50	No
		165	5825	14.31	14.50	No
	11ac40	151	5755	13.96	14.50	No
		159	5795	14.24	14.50	No
	11ac80	155	5775	14.30	14.50	Yes
	11ax20	149	5745	14.19	14.50	No
		157	5785	14.36	14.50	No
		165	5825	14.11	14.50	No
	11ax40	151	5755	14.30	14.50	No
		159	5795	13.91	14.50	No
	11ax80	155	5775	14.22	14.50	No

Note: When multiple channel bandwidth configurations in a frequency band have the same maximum tune-up output power, the test configuration is determined by applying the following steps sequentially.

1) The largest channel bandwidth configuration is selected among the multiple configurations in a frequency band with the same maximum tune-up output power.

2) When multiple transmission modes (802.11a/n/ac) have the same maximum tune-up output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n, and 802.11n chosen over 802.11ac .and 802.11n chosen over 802.11ac then 802.11ax.

8.2 Bluetooth

8.2.1 Bluetooth Output Power

Test Mode	Modulation	Channel	Frequency	AV power (dBm)	Tune-up (dBm)	SAR Test
BT	DH5	CH 0	2402	8.27	9.00	Yes
		CH 39	2441	8.24	9.00	No
		CH 78	2480	8.14	9.00	No
	2DH5	CH 0	2402	5.23	6.00	No
		CH 39	2441	5.55	6.00	No
		CH 78	2480	5.41	6.00	No
	3DH5	CH 0	2402	5.41	6.00	No
		CH 39	2441	5.59	6.00	No
		CH 78	2480	5.53	6.00	No
	BLE1M	CH 0	2402	4.93	5.50	No
		CH 19	2440	4.66	5.50	No
		CH 39	2480	4.64	5.50	No
	BLE2M	CH 1	2404	4.85	5.50	No
		CH 19	2440	4.79	5.50	No
		CH 38	2478	5.03	5.50	No
Note: Since bluetooth BR mode is the maximum output power mode, SAR measurements were performed with test software using DH5 modulation,and SAR measurement is not required for the EDR and LE. When the secondary mode is ≤ ¼ dB higher than the primary mode.						

8.2.2 Bluetooth Duty Cycle

The Bluetooth duty cycle is 57.67% as following figure, according to 2016 Oct. TCB workshop for Bluetooth SAR scaling need further consideration and the maximum duty cycle is 100%, therefore the actual duty cycle will be scaled up to 100% for Bluetooth reported SAR calculation.
Duty Cycle

