


Size: 96X80mm																																					
 																																					
Z-W88 Bluetooth Headset User's Manual Z-W88 Bluetooth Headset Operation Manual Thank you for using our company's sport Bluetooth headset product, for your fast, skilled operate of this product, easy, happy to use this product. Please read this manual carefully. Brief Introduction Wireless Bluetooth Technology The bluetooth equipment made with latest technology and can be connected with mobile, PDA, desktop computer, headset, mouse, keyboard, or other Bluetooth equipments wirelessly. It is commuante by letter 16000/s and choose the least deastate channel of the 79 channels. Z-W88 sport bluetooth headset features Slimly exterior, portable design. Enjoy your music during sport by stereo. The idea according to advanced technology. Get rid of disturbing cables, just by wireless. Pairing with mobile then you can cost off radiatization from mobile. Unique and intelligent function let you will not miss any mobile calls during you enjoy music.																																					
-1-																																					
Use Range - paired with the Bluetooth mobile, wireless enjoy mobile phone music, incoming call Linghu WU; - paired with PC (with Bluetooth function) or connect USB adapter, wireless enjoy network music; - paired with PC (with Bluetooth function) or connect USB adapter) wireless remote chat (support QQ, Skype, MSN, etc.). * Support iPhone 3G, iPhone 3GS; Wireless music transmission pairing & calling Accompanying Accessories * Z-W88 wireless stereo bluetooth headset * USB Charging cable * Operation Manual * Warranty Card (Optional Card) Start Use Headset built-in rechargeable lithium battery. Not full of energy in new headset's better. The first to use it, please charge it at least 4 hours to let it full of energy. After the first time using, can charge it 1-2 hours enough. When charging																																					
-2-																																					
Introduction to Bluetooth Equipments Pairing Pairing is a process to connect Bluetooth equipments each other. It will create a permanent and safe link between your equipments and provide them with quick service from Bluetooth without using any password. 1. First step: Headset status: Press S4 key for 5 seconds → red & blue lights flash quickly → headset with "di" sound → red light flash & blue light start flashing alternately → headset with "bi, bi, ..." sound → stop press S4 key → enter into pairing status. 2. Second step: Begin to pairing on your mobile (Please refer to mobile user manual). After searching you will get "Z-W88" in your mobile equipment list. 3. Third step: You will be required to enter Pin-Code → Password 0000 is needed to enter → Pairing successfully. (Note: 0000 is a default pairing Pin-Code for bluetooth headset)																																					
-4-																																					
Connected to stereo while the blue light flash once per second → the red light flash once per second; at this time connections on the stereo and mono → red & blue light flash per second at the same time once; if not connected, then enter the standby mode, the red light flashes continuously. 2. Shutdown headset 1) Start-up status: Press S4 key 3 seconds → red & blue lights flash quickly for one time → headset with "bi" sound → Shutdown. 2) When Searching the equipment or without the receive range of headset will automatically shutdown after not get any connection in 1 minute. Basic Use Method Dial, Talk & Finish calls After the bluetooth headset finish pairing with your mobile, you can use the headset to answer the phone or enjoy the mobile stereo music. Mobile dial, talk and finish a call Dial a call																																					
-6-																																					
volume... (From low to high total 15 levels, you can hear "Bi, Bi" when on low or on high) 5. Press S4 key shortly. Off key on mobile or the other side hang up the call to finish it → red light flashes slowly (around 1 time / second). After that, if connected stereo → Red & blue lights flash slowly → automatically turn to stereo status. Mobile Stereo music Play Mode Need to pairing the mobile and set it play the music by bluetooth stereo system. 1. Playing music, press S3 key quickly to Backward. 2. Playing music, press S2 key quickly to Upward. 3. Playing music, press S1 PLAY key quickly, music stops. Press S1 PLAY key quickly, music playing. Note: Base on different design for different mobiles, during the headset stand-by mode, the bluetooth connection may be automatically cut off. PC or PDA connect with headset The bluetooth headset can be also connected with PC or																																					
-8-																																					
Pairing with USB computer bluetooth dongle Stereo music play mode: 1) USB dongle insert into computer USB port, put the CD ROM into computer's CD room, setting program, after setting, re-start the computer, then setting successfully. 2) Pairing: First step: Plug the USB dongle into the computer's USB port → enter into pairing status → Red, blue lights flash alternately. Second step: Headset into pairing status (red & blue lights flashing alternately) Third step: Start-up → "My bluetooth" in the computer, searching the bluetooth equipment, then you can find the "Z-W88" equipment list. Fourth step: Choose "Z-W88" in the list, input the Pin-Code "0000" on the computer (Note: "0000" is the default pairing Pin-Code for bluetooth headset). Fifth step: Pairing successfully, red & blue light flash slowly (around 1 time / second).																																					
-9-																																					
Note: If the bluetooth headset isn't on pairing status, the USB bluetooth dongle cannot search the headset. Please set up the headset on pairing status then begin to use the USB bluetooth dongle to search. 1) Start-up the headset, after pairing successfully, start-up the computer's media player to play music. a. Playing music, press S3 to next backward song. b. Playing music, press S2 to next upward song. c. Playing music, press S1, music stopped, press S1 again, music played. Note: Use other USB bluetooth dongle may be missed some function, we suggest to use our special USB bluetooth dongle for our headset. Skype: 1) Start-up the headset, after pairing successfully, start-up skype on computer. 2) Dial number function: You can use the mouse to process with skype, or choose the person whose you want to call first, then press S4 for 2 seconds to call.																																					
-10-																																					
a. After communicate on QQ → Press S4 to finish the call (or press the finish key on QQ directly). b. When the call coming from QQ, if you don't want to answer the phone, you can press the refuse key on QQ directly. 6) After finish the call, the headset can automatically enter into the stereo mode to enjoy the music. Note: a. when using a headset with the Internet in the long-distance call, the Bluetooth adapter for other software is different, the use of methods of operation are also different. b. when using a headset with the Internet in the long-distance call if it's a silent call, please set call tool (QQ, Skype, MSN) of the audio settings for audio input and output in the Bluetooth status. Important Information 1. Red light flashes slowly? - The bluetooth headset is low power, please charge it as quick as possible. 2. The headset can not be start-up after charge for 20 minutes?																																					
-12-																																					
6. Can my bluetooth headset work with mobile of any model? - No. It can only work with mobile which has bluetooth. 7. What is the effective distance for headset and Bluetooth mobile? - Their maximum effective distance is 10 meters, but that may vary depending on specific environment or mobile specifications. Some mobile's effective distance may be less than 10 meters or only around 5 meters. 8. When my mobile is searching the headsets, why do several bluetooth equipments appear? - Within the effective distance, most Bluetooth mobile will search several Bluetooth equipments (like PDA, Notebook, ...) after their Bluetooth has been activated. When your mobile found them, "Z-W88" (or Unknown Equipment) will appear on your mobile. 9. Why can not my mobile find Bluetooth equipment? - If your headset has not been paired with other equipment, your mobile can not find any Bluetooth equipment. Before using a mobile, please refer to user manual, make sure equipment is paired. (Search you equipment for detailed instructions)																																					
-14-																																					
- It will not display the Incoming telegram when you dial numbers, or your mobile cannot support Incoming telegram displays. 15. Why different answer function with different software? - Different mobile make use different bluetooth module. For example, for T610, only need to press S4 gently to answer the call, however, for P800 and P900, you should press S4 for 3 seconds then can answer the phone. That cause by P800 and P900 are intelligent mobile, so a little different definition for using keys. Commonly, the use of answer phones are "press the key gently" or "press the key for 3 seconds". Headset Maintain * If use non-original accessories, it may cause capability come down, body hurted, short circuit or abate the maintain. * If assembly your bluetooth headset, it may cause the headset shatter or abate the maintain. * Don't place the headset on more dust range. * Use the clean, soft and dry fabric to clean your headset. * When you don't want to use the headset, please put it																																					
-16-																																					
* Base on room temperature using, can get the largest capability. * Using at outdoor temperature, will cause reduce the capability. * If headset do not use for long time, need to charge it 1 time at least per 2 months. Features and Specifications * Wireless enjoy stereo music playing * Wireless dial, talk, phone calls * Wireless enjoy stereo music from the computer * Use the Internet to achieve long-range wireless two-way communication; * Wireless enjoy stereo music, set aside to answer the call automatically converted; * High-fidelity, CD quality sound effects; * Remote control music playback status (remote control music playback, pause, up and down selections, volume control); * Clearly, sensitively, omni-directional microphone design, voice clarity, no echo;																																					
-18-																																					
Specification: <table border="1"> <thead> <tr> <th>Product Name</th><th>Wireless Bluetooth Stereo Headset</th></tr> </thead> <tbody> <tr> <td>Edition</td><td>V2.1+EDR</td></tr> <tr> <td>Frequency coverage</td><td>2.402GHz~2.480GHz ISM Band</td></tr> <tr> <td>Sensitivity</td><td>-80dbm</td></tr> <tr> <td>Wireless Transfer Standard</td><td>CLASS 2</td></tr> <tr> <td>Channel</td><td>79channels of 1MHz BW</td></tr> <tr> <td>Contact Terms</td><td>Point-to-Point</td></tr> <tr> <td>Transmit Range</td><td>≤10M</td></tr> <tr> <td>Frequency Response</td><td>20Hz-20KHz</td></tr> <tr> <td>S/N rate</td><td>80db</td></tr> <tr> <td>Speak power rate</td><td>2X10mW</td></tr> <tr> <td>Status indication</td><td>Red Led call status Blue Led stereo status, charging instructions</td></tr> <tr> <td>Pairing products</td><td>AD2P, ACVRP Bluetooth protocol of the computer, USB Bluetooth adapter, Bluetooth cell phones</td></tr> <tr> <td>Battery</td><td>Lion, 3.7V 150mA</td></tr> <tr> <td>Charge Time</td><td>1-2 hours</td></tr> <tr> <td>Charge Power</td><td>PC USB 150mA</td></tr> <tr> <td>Operate hours</td><td>>5 hours (battery saturation)</td></tr> <tr> <td>Size</td><td>15.5x13x5cm</td></tr> </tbody> </table>		Product Name	Wireless Bluetooth Stereo Headset	Edition	V2.1+EDR	Frequency coverage	2.402GHz~2.480GHz ISM Band	Sensitivity	-80dbm	Wireless Transfer Standard	CLASS 2	Channel	79channels of 1MHz BW	Contact Terms	Point-to-Point	Transmit Range	≤10M	Frequency Response	20Hz-20KHz	S/N rate	80db	Speak power rate	2X10mW	Status indication	Red Led call status Blue Led stereo status, charging instructions	Pairing products	AD2P, ACVRP Bluetooth protocol of the computer, USB Bluetooth adapter, Bluetooth cell phones	Battery	Lion, 3.7V 150mA	Charge Time	1-2 hours	Charge Power	PC USB 150mA	Operate hours	>5 hours (battery saturation)	Size	15.5x13x5cm
Product Name	Wireless Bluetooth Stereo Headset																																				
Edition	V2.1+EDR																																				
Frequency coverage	2.402GHz~2.480GHz ISM Band																																				
Sensitivity	-80dbm																																				
Wireless Transfer Standard	CLASS 2																																				
Channel	79channels of 1MHz BW																																				
Contact Terms	Point-to-Point																																				
Transmit Range	≤10M																																				
Frequency Response	20Hz-20KHz																																				
S/N rate	80db																																				
Speak power rate	2X10mW																																				
Status indication	Red Led call status Blue Led stereo status, charging instructions																																				
Pairing products	AD2P, ACVRP Bluetooth protocol of the computer, USB Bluetooth adapter, Bluetooth cell phones																																				
Battery	Lion, 3.7V 150mA																																				
Charge Time	1-2 hours																																				
Charge Power	PC USB 150mA																																				
Operate hours	>5 hours (battery saturation)																																				
Size	15.5x13x5cm																																				
-19-																																					
Z-W88蓝牙耳机使用说明 感谢阁下使用本公司出品的后挂式蓝牙立体声耳机，为了您能快速、熟练的操作本产品，轻松、愉快的使用本产品，请先认真、仔细阅读读本说明书。 简介 无线蓝牙技术 蓝牙是一种短距离无线通讯技术，它支持蓝牙设备之间的无线连接，如手机、PDA、电脑、耳机、鼠标、键盘、打印机等等。它的工作频率根据ISM标准2.4G-2.48G之间，通信时以每秒1600次的速度在79个频道上跳跃以选择干扰最小的通道，蓝牙技术的通信范围是10M(CLASS II标准)。 Z-W88运动型蓝牙耳机特点 外型采用美观、轻便的后挂式设计，在运动中也能听到美妙的立体声音质；先进的人体学设计耳挂，配戴舒适、方便；采用先进的蓝牙技术设计，																																					
-1-																																					
在使用中摆脱数据线缆的烦恼，与手机配对使用使您摆脱手机线缆的烦恼；独特的、高智能的功能设计，在欣赏音乐时也不错过每一个电话，使用更轻松、方便。 使用范围 * 与蓝牙耳机配对使用，无线欣赏手机音乐、接听来电两不误； * 与电脑（具有无线或连接USB适配器）配对使用，无线收听网络音乐； * 与电脑（具有无线或连接USB适配器）配对使用，也可通过蓝牙耳机（支持QQ、Skype、MSN等）； * 与支持iPhone 3G、iPhone 3GS无线音乐传输和无线通话设备连接。 包装清单 * Z-W88蓝牙耳机 * USB充电线 * 说明书 * 保修卡（选配卡）																																					
-2-																																					
S1 PLAY按键：播放 / 停止（立体声状态）；拒听（来电状态） S2 上一曲按键：上一曲（立体声状态）； S3 下一曲按键：下一曲（立体声状态）； S4 开关按键：电源开关，接听电话，结束电话，与其他设备配对； S5 音量增加按键：音量+； S6 音量减小按键：音量-； LED1 单声指示灯； LED2 立体声蓝色指示灯。 耳机与蓝牙设备的配对 在您使用您的蓝牙耳机之前必须与您的手机（或其他蓝牙设备）进行配对。 第一步：耳机在关机状态下按S4键5秒，耳机红灯亮1秒，耳机发出“嘀”声，红灯亮一次，当红色和蓝色指示灯开始交替闪烁时，耳机发出bi、bi两声，停止按S4键，耳机进入配对状态。																																					
-4-																																					
基本的使用方法 拨打、接听和结束电话 当蓝牙耳机和您的手机完成配对之后，您就可以使用耳机来接听电话或收听手机播放的立体声音乐。 手机拨出、接听和结束通话 拨出电话 使用手机的键盘拨号 1. 用您的手机按照和平时同样的方式拨号，连续按耳机将发出接听声，电话接通后，声音会自动切换到蓝牙耳机，接通后红灯慢闪（约每秒闪烁一次）。 2. 选定或手机输入完您要拨出的电话，按S4键两次，连续按耳机将发出接听声，电话接通后，声音会自动切换到蓝牙耳机，接通后红灯慢闪（约每秒闪烁一次）。 接听电话 1. 当您手机的来电时，耳机将发出“bi”声，红、蓝两灯同时缓慢闪烁，单声、立体声连接成功。如只有红灯慢闪，则只有单声连接成功；如只有蓝灯慢闪，则只有立体声连接成功。未连接成功则相应的连接操作。（约每秒闪烁一次） 拒接电话 1. 当您手机的来电时，耳机将发出“bi”声，红、蓝两灯同时缓慢闪烁，单声、立体声连接成功。如只有红灯慢闪，则只有单声连接成功；如只有蓝灯慢闪，则只有立体声连接成功。未连接成功则相应的连接操作。（约每秒闪烁一次） QQ、Skype、MSN等网络通话 1. 当您手机的来电时，耳机将发出“bi”声，红、蓝两灯同时缓慢闪烁，单声、立体声连接成功。如只有红灯慢闪，则只有单声连接成功；如只有蓝灯慢闪，则只有立体声连接成功。未连接成功则相应的连接操作。（约每秒闪烁一次）																																					
-5-																																					
耳机的开关 1. 耳机的开机 关机状态下按S4键2秒，红、蓝色指示灯亮1秒，红灯闪烁一次，耳机发出“嘀”声，红灯闪烁，停止按S4键，耳机完成，进入连接模式；自动搜索已配对设备，连接上立体声则蓝色指示灯每秒闪烁一次；连接上单声则红色指示灯每秒闪烁一次；同时连接上立体声和单声则红、蓝色指示灯每秒同时闪烁一次；如都没有连接上，则进入待机模式，蓝色指示灯连续闪烁。 2. 关闭耳机 1. 在待机状态，按下S4键3秒，红、蓝色指示灯快速闪烁一次，耳机发出“嘀”声，耳机接收。 2. 在待机连接设备状态下离开耳机的接收范围，3秒钟后没找到连接设备自动关机。																																					
-6-																																					
接听和结束通话 当您电话打进来时，您会听到耳机“嘀、嘀”提示音，耳机红色指示灯常亮。 1. 电话接听时：短按一次S4键或按手机接听键可接听电话，接通电话后红灯慢闪（约每秒闪烁二次）。 2. 通话中：按S1键一次，转到手机电话，再按S1键一次又转到手机接听电话（有部分手机可能不支持接听电话，无法完成通话接听）。 3. 电话接听时：短按一次S4键可拒绝接听来电。 4. 通话时按一次音量增加键（S5），为增大音量一般，按一次音量减小键（S6），为降低音量一般（从最小音量共有15级，到最大和最小音量您都能听到“bi”声）。 5. 短按一次S4键、手机挂机键或者对方挂机可以结束通话，通话结束后红灯慢闪（约每秒闪烁一次），如连接有立体声将红、蓝灯同时慢闪。																																					
-8-																																					
USB电脑蓝牙适配器与耳机连接 立体声音乐播放模式 1. USB蓝牙适配器插入电脑USB端口，安装光盘放入电脑光驱，运行安装程序，安装完毕，重新启动电脑，安装完成。 2. 配对： 第一步：将USB蓝牙适配器插入电脑USB端口； 第二步：耳机进入配对状态（红、蓝灯交替闪烁）。 第三步：打开电脑中的“我的蓝牙”，搜索蓝牙设备，搜索完成后您将会在设备列表中找到名为“Z-W88”的新设备。 第四步：选择“Z-W88”，您将会被要求输入配对码（Pin-Code），请在电脑上输入蓝牙耳机的配对码：0000，配对过程就完成了。（注：0000 是蓝牙耳机的固定预设配对码） 第五步：配对成功，红灯缓慢闪烁（约每秒闪烁一次）。																																					
-10-																																					
方法可能有所不同。 skype通话 1. 打开耳机，连接成功后，电脑打开skype。 2. 去拨号功能：通过鼠标对skype进行操作，也可以先选择要联系的人，然后按S4键2秒拨出。 3. 语音通话功能：skype来电后，鼠标传到蓝牙耳机上，操作蓝牙耳机上S4键接听来电，接听成功（也可通过skype接听键完成），skype界面上会显示相应的正在通话状态。 4. 挂断/拒绝来电的功能：当skype来电后，在接听关闭，操作耳机上的S4键结束通话（也可通过skype来电时，若是不想接听此来电，可操作skype界面上的拒绝键来对来电的拒绝/挂断）。 5. 当skype来电时，若是不想接听此来电，可操作skype界面上的拒绝键来对来电的拒绝/挂断。 6. 通话结束后耳机自动转到立体声模式欣赏音乐。 QQ通话 1. 打开耳机，连接成功后，电脑打开QQ；																																					
-12-																																					
b. 在使用耳机利用网络远程通话时，如通话无声，请将通话工具（QQ、Skype、MSN）的音频设置的音频输入、输出均设置为蓝牙状态。 常见问题 1. 红色指示灯缓慢闪烁？ 说明蓝牙耳机电量不足，请尽快给耳机充电。 2. 充电二十分钟后耳机不能开机？ 蓝牙耳机至少充电40分钟后才能开机，强烈建议使用耳机将电池充满。 3. 充电时没有指示？ 如果耳机电池用尽或者长时间不使用后首次充电，开始几分钟可能没有充电指示，稍等之后红色指示灯就会亮起指示充电。 4. 耳机中没有声音？ - 确定耳机与手机已配对成功																																					
-14-																																					
部会被搜索到（比如PDA、笔记本电脑……），可能显示“Z-W88”或者“未知设备”。 9. 为什么我的手机配对时不能搜索到我的蓝牙耳机？ 如果蓝牙耳机不在配对状态下，则不能被搜索到。请将蓝牙耳机于配对状态。 10. 是否每次使用蓝牙耳机都要进行配对？ 不需要，蓝牙耳机和手机仅在第一次使用时需要配对，之后即使设备关闭也不需要再次配对。 11. 为什么耳机会有杂音？ 通话质量将受到以下两方面的影响 如果手机与手机信号比较微弱，通话质量也会相应比较差。 * 手机和耳机的距离超过标准距离也会增大杂音 * QQ、skype的通话质量将受网络的影响。 12. 如果耳机听不清楚怎么办？ 调节手机上的音量或者按耳机的音量增加键以增大音量，同时注意您的手机信号是否足够。																																					
-16-																																					
电气短路及保护的失效。 * 分解拆卸您的蓝牙耳机可能会导致耳机损坏，不要将耳机置于灰尘较多的环境下。 * 使用干净、柔软、干燥的布清洁您的耳机。 * 不使用耳机时将耳机置于原包装内。 * 不要让孩子玩耍耳机，他们可能伤害自己或者损坏耳机。 * 不要将耳机置于过热或者过冷的环境中，否则耳机有可能暂时无法使用。 旅行充电器 * 充电器仅被设计成室内使用，请勿在室外使用。 * 充电器只能使用标准的输入电压。 * 从插座上拔出充电器时请勿拉扯电线，否则可能损坏充电器。 电池相关信息 新电池																																					
-18-																																					
停、上下乐曲、音量调节）； * 高灵敏度、全向型麦克风设计，语音清晰、无回音。 产品规格及参数： <table border="1"> <thead> <tr> <th>产品名称</th><th>运动型蓝牙耳机</th></tr> </thead> <tbody> <tr> <td>版本</td><td>蓝牙耳机 V2.1+EDR</td></tr> <tr> <td>频率范围</td><td>2.402GHz~2.480GHz ISM Band</td></tr> <tr> <td>接收灵敏度</td><td>-80dbm</td></tr> <tr> <td>无线发射标准</td><td>CLASS 2</td></tr> <tr> <td>频道</td><td>79channels of 1MHz BW</td></tr> <tr> <td>连接方式</td><td>点对点</td></tr> <tr> <td>发射功率</td><td>≤10M</td></tr> <tr> <td>频率响应</td><td>20Hz-20KHz</td></tr> <tr> <td>信噪比</td><td>80db</td></tr> <tr> <td>喇叭输出功率</td><td>2X10mW</td></tr> <tr> <td>状态指示</td><td>红色LED通话状态 蓝色LED立体声状态，充电指示</td></tr> <tr> <td>适用配对产品</td><td>符合AD2P、ACVRP蓝牙协议的手机、PDA、笔记本电脑、USB蓝牙适配器、蓝牙耳机等</td></tr> <tr> <td>电池</td><td>聚合物锂离子电池 3.7V 150mAh</td></tr> <tr> <td>充电时间</td><td>1-2小时</td></tr> </tbody> </table>		产品名称	运动型蓝牙耳机	版本	蓝牙耳机 V2.1+EDR	频率范围	2.402GHz~2.480GHz ISM Band	接收灵敏度	-80dbm	无线发射标准	CLASS 2	频道	79channels of 1MHz BW	连接方式	点对点	发射功率	≤10M	频率响应	20Hz-20KHz	信噪比	80db	喇叭输出功率	2X10mW	状态指示	红色LED通话状态 蓝色LED立体声状态，充电指示	适用配对产品	符合AD2P、ACVRP蓝牙协议的手机、PDA、笔记本电脑、USB蓝牙适配器、蓝牙耳机等	电池	聚合物锂离子电池 3.7V 150mAh	充电时间	1-2小时						
产品名称	运动型蓝牙耳机																																				
版本	蓝牙耳机 V2.1+EDR																																				
频率范围	2.402GHz~2.480GHz ISM Band																																				
接收灵敏度	-80dbm																																				
无线发射标准	CLASS 2																																				
频道	79channels of 1MHz BW																																				
连接方式	点对点																																				
发射功率	≤10M																																				
频率响应	20Hz-20KHz																																				
信噪比	80db																																				
喇叭输出功率	2X10mW																																				
状态指示	红色LED通话状态 蓝色LED立体声状态，充电指示																																				
适用配对产品	符合AD2P、ACVRP蓝牙协议的手机、PDA、笔记本电脑、USB蓝牙适配器、蓝牙耳机等																																				
电池	聚合物锂离子电池 3.7V 150mAh																																				
充电时间	1-2小时																																				
-20-																																					
13. 为什么我的耳机突然不能工作了？ 可能是因为耳机的电量不足了，电量不足时红色指示灯会闪烁，耳机发出“嘀、嘀”提示音。 14. 为什么我不使用来电显示的电话？ 拨打时不用来电显示的电话，您的手机不支持来电显示。 15. 为什么不同手机的电话接听方式不同？ 这是因为不同手机的电话接听方式不同，有的蓝牙耳机支持来电显示，有的不支持。如果您的蓝牙耳机支持来电显示，请在手机的来电显示设置中，将来电显示设置为蓝牙耳机。如果您的蓝牙耳机不支持来电显示，请在手机的来电显示设置中，将来电显示设置为手机。 16. 为什么我的蓝牙耳机不能接听电话？ 可能是因为耳机的电量不足了，电量不足时红色指示灯会闪烁，耳机发出“嘀、嘀”提示音。 17. 为什么我的蓝牙耳机不能接听电话？ 可能是因为耳机的电量不足了，电量不足时红色指示灯会闪烁，耳机发出“嘀、嘀”提示音。																																					
-21-																																					

FCC WARNING

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: Any changes or modifications not expressly approved by the manufacturer could void the user's authority to operate the equipment.

NOTE 2: The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.